# MTL4649/Y ISOLATING DRIVER

two-channel, for 4–20mA, HART® valve positioners with line fault detection

The MTL4649 accepts 4/20mA floating signals from a controller to drive 2 current/pressure converters (or any other load up to  $800\Omega$ ). For HART valve positioners, the module also permits bi-directional transmission of digital communication signals. Process controllers with a readback facility can detect open or short circuits in the field wiring: if these occur, the current taken into the terminals drops to a preset level. The MTL4649Y is very similar except that it provides open circuit detection only (i.e. no short-circuit detection).

## **SPECIFICATION**

See also common specification

**Number of channels** 

Two

Working range

4 to 20mA

Digital signal bandwidth

500Hz to 10kHz

Maximum load resistance

800Ω (16V at 20mA)

Minimum load resistance

 $90\Omega$  (short-circuit detection at  $< 50\Omega$ )

**Output resistance** 

 $> 1M\Omega$ 

Under/over range capability

Under range = 1mA

Over range = 24mA (load  $\leq 520\Omega$ )

Input and output circuit ripple

<40µA peak-to-peak

Communications supported

HART

Transfer accuracy at 20°C

Better than 20µA

Temperature drift

 $< 1.0 \mu A/^{\circ} C$ 


Input characteristics

Field wiring state	MTL4649	MTL4649Y
Normal	< 6.0V	< 6.0V
Open-circuit	< 0.9mA	< 0.5mA
Short-circuit	< 0.9mA	N.A.

# Response time

Settles within 200 $\mu A$  of final value within 100ms

#### MTL4649 / MTL4649Y



### **LED** indicator

Green: power indication

Maximum current consumption (with 20mA signals into 250 $\Omega$  load) 70mA at 24V dc

Power dissipation within unit (with 20mA signals into 250 $\Omega$  load) 1.6W at 24V

## SIL capable

These models have been assessed for use in IEC 61508 functional safety applications. See data on MTL web site.

The given data is only intended as a product description and should not be regarded as a legal warranty of properties or guarantee. In the interest of further technical developments, we reserve the right to make design changes.

